



# **Serial Interface Communication Protocol**

**for Models: Ultra Slim Profile [USP series]**

# Serial Control Protocol

## Serial Setup

Item	Settings
Baud rate	9600bps
Data Bit	8bit
Stop Bit	1bit
Parity Bit	None
Stream Control	None

## Command List

Power ON (Back Light On)									
73	65	74	62	6C	6F	6E	20	31	0D
Hex									

Power OFF* (Back Light Off)									
73	65	74	62	6C	6F	6E	20	30	0D
Hex									

\*Do not use the power button on the side of the display

Input Source Toggle* (Android Board – HDMI Mode) Loop									
73	65	74	73	6F	75	72	63	65	0D
Hex									

\*When no active HDMI input is detected, the display will revert to the Android board as a source

